

# Update 8-Server to Release 5.23.17 and above

## Pull

Pull the repository as always.

## Run Update

Run the update script:

```
C:\8Server\deploy\OEM\JTEL\copy_keyfile_en_mcp_v67.cmd
```

## Config Changes - StdCall\_MCP.cfg

### From new releases from 5.23.13 and onwards

You will need to make one change to the config file.

- Startup\_Command10

This should be changed to the following:

```
string Startup_Command10 = "c:/8Server/gi2/bin/giHal.exe -w -prosodyTransceiverThreadCount:32";
```

### From old releases prior to 5.23.13

If you are updating from a very old release, then several changes will be needed to **StdCall\_MCP.cfg**

**In this case it's better to take the new config, and make the changes manually. The following entries need to be considered:**

- Default\_SIP\_Contact
- Total\_Channel\_Count
- Inbound\_Use\_Channels
- Outbound\_Use\_Channels
- RFC2833\_DTMF\_Detection