

Update 8-Server to Release 5.23.17 and above

Pull

Pull the repository as always.

Run Update

Run the update script:

```
C:\8Server\deploy\OEM\JTEL\copy_keyfile_en_mcp_v67.cmd
```

Config Changes - StdCall_MCP.cfg

From new releases from 5.23.13 and onwards

You will need to make one change to the config file.

- Startup_Command10

This should be changed to the following:

```
string Startup_Command10 = "c:/8Server/gi2/bin/giHal.exe -w -prosodyTransceiverThreadCount:32";
```

From old releases prior to 5.23.13

If you are updating from a very old release, then several changes will be needed to **StdCall_MCP.cfg**

In this case it's better to take the new config, and make the changes manually. The following entries need to be considered:

- Default_SIP_Contact
- Total_Channel_Count
- Inbound_Use_Channels
- Outbound_Use_Channels
- RFC2833_DTMF_Detection