# **Aculab Licences**

The aculab licences, used for the telephony SIP / RTP layer, are present on the windows machine.

The initial installation of licences will be performed by jtel, as this involves accessing the jtel account on the aculab licencing portal.

However, movement or manual renewal of licences can be performed at a later date by the customer if desired.

NOTE: to enable smooth operation of aculab licences, the machine should always have an internet connection, WITHOUT a proxy server.

Access to servuk41.aculab.com and servus42.aculab.com on port 443 (https) are required.

## Movement of Licences

### On the old machine

On the machine from which the licences are to be removed:

Start the ACT. In the menu, under "Options" select "Enable removal of licences".

<b>5</b>		Aculab V6 ACT - Lic	ence Manager
<u>H</u> elp <u>O</u> ptions			
	licences		
Care Disable warnings o	n cancel and exit		
Clarking Settings	Product	Expiry Date and Time	Max Licences
Diagnostics	ProsodySv3:10000		
IP Settings IP Settings Licence Manager Prosody S Prosody T Prosody X HPI Configuration TiNG Settings	<ul> <li>Product Licences</li> </ul>		38 Total Licences
	1	18/Aug/2018 @ 10:31:54	10 Bi-direct Calls
	2	18/Aug/2018 @ 10:32:22	10 Bi-direct Calls
	3	18/Aug/2018 @ 10:32:49	10 Bi-direct Calls
	4	29/Sep/2018 @ 12:27:34	4 Bi-direct Calls
	5	08/Apr/2019 @ 20:44:43	4 Bi-direct Calls
	Feature: Video		0 Total Licenses
	SS7		
	Product Licences		0 Total Licences
	Feature: M3UA		0 Total Licenses
	SIP		
	Product Licences		0 Total Licences

Next, select the licence which should be removed, and click "Remove".

<b>S</b>		Aculab V6 ACT - Lic	cence Manager
<u>H</u> elp <u>O</u> ptions			
Views	Licence Manager		
Card List Clocking Settings Diagnostics IP Settings <b>Licence Manager</b> Prosody S Prosody T Prosody X HPI Configuration TiNG Settings	Product ProsodySv3:10000 Product Licences 1 2 3 4 5 Feature: Video SS7 Product Licences Feature: M3UA SIP Product Licences Feature: DRSS	Expiry Date and Time 18/Aug/2018 @ 10:31:54 18/Aug/2018 @ 10:32:29 18/Aug/2018 @ 10:32:49 29/Sep/2018 @ 12:27:34 08/Apr/2019 @ 20:44:43	Max Licences 38 Total Licences 10 Bi-direct Calls 10 Bi-direct Calls 10 Bi-direct Calls 4 Bi-direct Calls 4 Bi-direct Calls 0 Total Licenses 0 Total Licences 0 Total Licences 0 Total Licences 0 Total Licenses
Save Settings			
Apply Settings			
Exit	Renew		

#### Confirm the warning:



In the next screen, select copy to clipboard. This is the key you require, to install the licence on the new machine.



#### On the new machine

On the new machine, start the ACT, and select Licence Manager, and ProsodySv3:

elp <u>O</u> ptions			
Views	Licence Manager		
Clocking Settings	Product Exp ProsodySv3:100000	iry Date and Time	Max Licence
Diagnostics IP Settings Licence Manager Prosody S Prosody T Prosody X HPI Configuration TiNG Settings	<ul> <li>→ Product Licences Feature: Video</li> <li>SS7</li> <li>→ Product Licences</li> <li>Feature: M3UA</li> <li>SIP</li> <li>→ Product Licences</li> <li>Feature: DRSS</li> </ul>		10 Total Li 0 Total Lic 0 Total Lic 0 Total Lic 0 Total Lic 0 Total Lic
Save Settings Apply Settings Exit	Renew     Remove		Install

Click "Install" and paste the licence key from the old machine. Hit OK.

⁄ ACT - Licence Key Input	?	$\times$
Licence Key:		
	<u>o</u> k	<u>C</u> ancel

After contacting the licence server, the licence will install.

The next step, is to enable 8-Server to use the new licences, via the configuration files giAculab.cfg and StdCall\_MCP.cfg