

Table Reference - StatisticsClick2DialNoPortal

Contents

A record is made in this table every time the Click to Dial No Portal function is used.

This feature is not supported and may be removed in a future release.

Fields

Field	Type	Meaning
ID	INT	A unique ID assigned to each record.
ClientsID	INT	The ID of the Client via which the request was made.
DestinationNumber	VARCHAR	The destination number dialed.
Timeout	INT	The defined timeout value when the call was made.
CallerNumber	VARCHAR	The caller number used.
Caller	VARCHAR	The caller parameter used.
UserData	TEXT	The user data associated with the request.
dtSeizure	TIMESTAMP	The date and time the outbound call seized the circuit (the call was initiated).
dtAlert	TIMESTAMP	The date and time the outbound call received an alert (ringing) from the network.
dtConnect	TIMESTAMP	The date and time the outbound call was connected.
dtIdle	TIMESTAMP	The date and time the circuit went idle (end of call).
CallMilliseconds	INT	Call length in milliseconds. Note, it is not recommended to use this field, as this value can be calculated using the following formula: <code>TIMESTAMPDIFF(MICROSECOND, dtConnect, dtIdle)</code>
CONNRES	INT	The CONNRES value associated with the call. See Value Reference - CONNRES
ConnresText	VARCHAR	A text describing the CONNRES value.
ConnresCause	VARCHAR	The cause associated with the outcome of the call in internal jtel telephony server format.
ConnresCauseQ850	INT	The cause code according to Q.850 for the result of the outbound call.
ConnresCauseText	VARCHAR	A text description of the ConnresCause value.