

Table Reference - StatisticsPartTI

Content

This table contains CDR data read from the innovaphone PBX CDR connector.

Note: this table should be used with caution, as it is not always possible to match records to jtel ACD call records.

Note: this table is not supported by jtel support, enquiries regarding the contents of this table are strictly processed on a consulting basis only.

For a reference of the fields supplied by Innovaphone, please see http://wiki.innovaphone.com/index.php?title=Reference11r1:Concept_Call_Detail_Record_CDR_PBX.

Fields

Field	Type	Meaning
ID	INT	A unique ID assigned to each record.
Name	VARCHAR	The cn attribute of the reported CDR.
Number	VARCHAR	The e164 attribute of the reported CDR.
ShortName	VARCHAR	The h323 attribute of the reported CDR.
bOutbound	BOOLEAN	If the dir attribute of the reported CDR is "to" then bOutbound = FALSE (0). TRUE (1) otherwise.
bBusy	BOOLEAN	If the cause attribute of the reported CDR is 17 , then bBusy = TRUE (1), FALSE (0) otherwise.
bExternal	BOOLEAN	If the type attribute of the reported CDR is ext , then bExternal = TRUE (1), FALSE (0) otherwise. Additionally as a workaround for a presumed bug in the Innovaphone CDRs, when the h323 element is empty on receipt of alert-to or rel-from , then this field is also set to TRUE (1).
RemoteParty	VARCHAR	The e164 attribute of the reported CDR.
dtCreated	TIMESTAMP	The date and time on which the CDR record was created.
nRingSeconds	INT	The number of seconds the call was ringing for.
nConnSeconds	INT	The number of seconds the call was connected for.
nReleaseSeconds	INT	The number of seconds after the call was started when it was released.
nEnquirySeconds	INT	The number of seconds the call was in enquiry status, if a call transfer was performed or aborted.
bRelease	BOOLEAN	If the call was released (disconnected) by the local party (the cn) then TRUE (1), FALSE (0) otherwise.
bCallRefused	BOOLEAN	If the call was rejected by the receiving party then TRUE (1), FALSE (0) otherwise.
cfFromName	VARCHAR	The dn attribute of the cf tag if a call forward was indicated.
cfFromNumber	VARCHAR	The e164 attribute of the cf tag if a call forward was indicated.

cfFromShortName	VARCHAR	The h323 attribute of the cf tag if a call forward was indicated.
remoteName	VARCHAR	The dn attribute received in the alert-to or alert-from message.
remoteNumber	VARCHAR	The e164 attribute received in the alert-to or alert-from message.
remoteShortName	VARCHAR	The h323 attribute received in the alert-to or alert-from message.
ctFromName	VARCHAR	In the case of a transfer-to event, the value of the dn attribute of the CDR,
ctFromNumber	VARCHAR	In the case of a transfer-to event, the value of the e164 attribute of the CDR.
ctFromShortName	VARCHAR	In the case of a transfer-to event, the value of the h323 attribute of the CDR.
ctToName	VARCHAR	The dn attribute of the ct tag or to tag if present.
ctToNumber	VARCHAR	The e164 attribute of the ct tag or to tag if present.
ctToShortName	VARCHAR	The h323 attribute of the ct tag or to tag if present.
XMLData	TEXT	The XML data supplied to the CDR endpoint.
dtLastModified	TIMESTAMP	The date and time at which this entry was last modified.